



# TK-2360/3360

**Compact VHF/UHF FM Portable Radios** 

FleetSync®



## **GENERAL FEATURES**

- 5W (136-174 MHz)
- 5W (450-520, 400-470 MHz)
- 16 Conventional Channels
- Single Priority / Normal Scan
- Transmit / Busy / Call Alert / Scan / Warn LED
- 4-Color LED (Blue/Red/Green/Orange)
- 3 PF Keys (w/Hold Function)
- Orange Emergency / AUX Key
- 500 mW Audio Power
- Enhanced Kenwood Audio
- Companded Audio (per CH)
- Voice CH# Announcement
- VOX ready
- Voice Inversion Scrambler Built-in
- 16 Scrambler Codes (per CH)
- Emergency Call Features
- Emergency Man-Down Option
- Lone Worker Alert
- QT / DQT
- Two-Tone Decode¹
- Single / Two-Tone Encode¹
- DTMF Encode / Decode<sup>2</sup>

- Special Alert Tone Pattern³
- Time Out Timer
- Busy Channel Lockout
- Low Battery Warning
- Battery Saver
- Windows Programming & Tuning<sup>4</sup>
- Password Protection
- MIL-STD-810 C/D/E/F
- IP-54/55 Water & Dust Intrusion
- Intrinsically Safe Option

### FleetSync®

- PTT ID Digital ANI
- Selective Call & Group Call<sup>5</sup>
- Paging Call
- Status Messaging<sup>5</sup>
- Emergency Status

## **MDC-1200**

- PTT ID Digital ANI
- Emergency Status
- Radio Check
- Radio Inhibit

## **Options**

**■ KNB-55L** Li-ion Battery Pack (1,480mAh)

KNB-56N Ni-MH Battery Pack (1,400mAh)

■ KNB-57L Li-ion Battery Pack (2,000mAh)

**■ KNB-40LCV** Li-ion Battery Pack (1,950mAh)

■ KBP-5 **Battery Case** 

KSC-25 Rapid Charger

KSC-30 Regular Charger for KNB-56N



KNB 55L



**■** KRA-23 UHF Low Profile Helical Antenna

■ KSC-256K

Six Unit Gang Charge

■ KRA-26 VHF Helical Antenna

**KRA-27** UHF Whip Antenna

**KMC-45** Speaker Microphone





Earphone Kit for

KMC-45 (2.5mm plug)

Regular Rate Vehicular

Rapid Rate Vehicular

Charger Adapter

Charger Adapter

(for KSC-30)

(for KSC-25)

■ KVC-4

■ KEP-2

■ KHS-22

Head Set

KVC-3



кус-з

KHS-7A Lightweight Single Muff Headset



**■ KHS-8BL** 2-wire Palm Mic with Earphone (Black)



**■ KHS-9BL** 3-wire Lapel Mic with Earphone (Black)



■ KLH-138 Leather Case



■ KBH-12 Belt Clip



# **Specifications**

All accessories and options may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories and options.

ENERAL				
equency Range				
Type 1	136-174 MHz	450-520 MHz		
Type 2	_	400-470 MHz		
umber of Channels	Max	Max. 16		
hannel Spacing				
Wide/Narrow	25, 30kHz/12.5,15kHz	25kHz/12.5kHz		
perating Voltage	7.5V D	C±20%		
attery Life (5-5-90 duty cy	cle, save off)			
with KNB-55L (1480 m.	Ah) Approx	Approx. 9 hours		
with KNB-56N (1400 m	Ah) Approx	Approx. 9 hours		
with KNB-57L (2000 m.	Ah) Approx.	Approx. 13 hours		
perating Temperature Ran	ige -22°F ~ +140°	-22°F ~ +140°F (-30°C ~ +60°C)		
	[-14°F ~ +140°	°F (-10°C ~ +60°C)		
	when KNB-5	5L/57L in use]		
equency Stability	±2.5ppm (-2	±2.5ppm (-22°F ~ +140°F)		
ntenna Impedance	50	50 Ω		
hannel Frequency Spread				
	38MHz	70MHz		
imensions (W x H x D), Pro	ojections not included			
Radio Only		2.2" x 4.1" x 0.55" (56 x 103.7 x 14.0mm)		
with KNB-55L		2.2" x 4.1" x 1.14" (56 x 103.7 x 29.1mm)		
with KNB-56N		2.2" x 4.1" x 1.33" (56 x 103.7 x 33.8mm)		
with KNB-57L	2.2" x 4.1" x 1.18" (	2.2" x 4.1" x 1.18" (56 x 103.7 x 30.1mm)		
/eight				
Radio Only		5.75oz (163g)		
with KNB-55L		9.17oz (260g) without antenna		
with KNB-56N		12.70oz (360g) without antenna		
with KNB-57L	10.05oz (285g	10.05oz (285g) without antenna		
C ID				
Type 1	ALH415000	ALH415100		

Model	TK-2360	TK-3360		
RECEIVER (Measurements made	per TIA/EIA-603)			
Sensitivity (12dB SINAD)				
Wide/Narrow	0.25µV	/0.28µV		
Selectivity				
Wide/Narrow	70dB	/63dB		
Intermodulation Distortion				
Wide/Narrow	68	8dB		
Spurious Response	70	)dB		
Audio Distortion	Less th	ıan 5%		
Audio Output	500 mV	500 mW / 8 Ω		
TRANSMITTER (Measurement	s made per TIA/EIA-603)			
RF Power Output				
High/Low	5W .	/ 1W		
Spurious Response	70	)dB		
Modulation				
Wide/Narrow	16KØF3E	16KØF3E/11KØF3E		
FM Noise				
Wide/Narrow	45/4	43dB		
Audio Distortion	Less th	Less than 5%		

Specifications are subject to change without notice, due to advancements in technology.

Windows® is a registered trademark of Microsoft Corporation in the United States and other countries. FleetSync® is a registered trademark of JVC KENWOOD Corporation in the United States and/or other countries. All other trademarks are property of their respective owners.

# **Applicable MIL-STD & IP**

Standards	Methods/Procedures MIL-STD 810C	Methods/Procedures MIL-STD 810D	Methods/Procedures MIL-STD 810E	Methods/Procedure MIL-STD 810F
Low Pressure	500.1/Procedure I	500.2/Procedure I, II	500.3/Procedure I, II	500.4/Procedure I, II
High Temperature	501.1/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II
Low Temperature	502.1/Procedure I	502.2/Procedure I, II	502.3/Procedure I, II	502.4/Procedure I, II
Temperature Shock	503.1/Procedure I	503.2/Procedure I	503.3/Procedure I	503.4/Procedure I, II
Solar Radiation	505.1/Procedure I	505.2/Procedure I	505.3/Procedure I	505.4/Procedure I
Rain	506.1/Procedure I, II	506.2/Procedure I, II	506.3/Procedure I, II	506.4/Procedure I, III
Humidity	507.1/Procedure I, II	507.2/Procedure II, III	507.3/Procedure II, III	507.4
Salt Fog	509.1/Procedure I	509.2/Procedure I	509.3/Procedure I	509.4
Dust	510.1/Procedure I	510.2/Procedure I	510.3/Procedure I	510.4/Procedure I, III
Vibration	514.2/Procedure VIII, X	514.3/Procedure I	514.4/Procedure I	514.5/Procedure I
Shock	516.2/Procedure I, II, V	516.3/Procedure I, IV	516.4/Procedure I, IV	516.5/Procedure I, IV
International Protec	tion Standard			
Dust & Water Protection	IP54/55			

ALH415101

- footnotes from Front:

  1 Two-Tone Decode (3 sets x 2 pairs each); Single / Two-Tone
  Encode (1 tone).

  2 DTMF Encode: PTT ID, Emergency ANI, Auto-Dial (8 numbers),
  DTMF Decode: Selective Call (10-digit ID Code, Group Codes;
  A, B, C, D & Wild Card characters), and Radio Stun.

  3 Special Alert Tone Pattern operates for 2-Tone, DTMF, FleetSync\*
  selective call decode.

  4 KPG-128D required: Windows\* 2000/XPIVista compatible.

  5 ID List capacity is 8 ID's; 10 Group ID's; Status 1 & 2 (10-99).

\*To meet IP54/55, the 2-pin connector cover has to be connected on the radio or the locking bracket has to be attached to the KMC-45 external speaker microphone.



#### Kenwood U.S.A. Corporation

**Communications Sector Headquarters** 

3970 Johns Creek Court, Suite 100, Suwanee, GA 30024-1265

Order Administration/Distribution



